



NESS ACCESS CONTROL PRODUCTS

Ness IDTeck Accessories

DATA CONVERTERS

SPECIFICATIONS	101-122
CPU	Ubicom SX52BD/PQ 50Mhz (8-Bit MicroController, 50MIPS)
MEMORY	4K Bytes Flash Program Memory 256 Bytes SRAM Data Memory 2KBytes Flash Memory (Web Page & System Parameter)
NETWORK CONNECTION	10 Base-T Ethernet Interface
NETWORK PROTOCOL	HTTP, TCP/UDP, IP/ICMP/ARP IEEE 802.3 (Ethernet)
UTILITY SOFTWARE	NetEye Setup Program (Windows98/ME/NT/2000) NetEye Search, IP Setup, Built-In Test Result Display, Web Page Upload on the Network Loop Test Program (Windows95/98/ ME/NT/2000)
POWER REQUIREMENTS	6-9V DC



101-122 NetEye 1000SA

- External Serial to Ethernet Converter
- Miniaturized module device for Network connectivity
- TCP/IP Kernel and Ethernet installed
- RS232, RS422, RS485 (optional) supported

SPECIFICATIONS	101-121
COMMUNICATION	RS-232 (DB-9Pin, Male) Maximum distance, 20m
LED INDICATORS	Power / TXD / RXD
COMMUNICATION SPEED	115.2 KBPS
POWER SUPPLY	240V AC



101-121 CNP200A

- RS232 signal converter to RS422/485
- Multi drop or Point to Point Communication type
- Built in Surge Protector
- Built in LED (Power, Transmit, Receive)

www.ness.com.au

© 2004 Ness Security Products Pty Ltd ABN 28 069 984 372
Photographs are used for illustrative purposes only. Design and specifications may vary.



Access Control Products



Quality
Endorsed
Company
ISO9001
LIC No. QSC2074
NSW Head Office only

SYDNEY
02 8825 9222
sales@ness.com.au

MELBOURNE
03 9875 6400
nessmelb@ness.com.au

BRISBANE
07 3399 4910
nessbris@ness.com.au

PERTH
08 9328 2511
nessper@ness.com.au

ADELAIDE
08 8277 7255
aquavia@cobweb.com.au

NZ (NFS SECURITY)
+64 9 573 0401
sales@nfs.co.nz