

R12 Radio PIR



- 12M X 12M WIDE ANGLE COVERAGE
- SAWR STABILISED RADIO TRANSMITTER
- HIGH R.F. AND E.S.D. IMMUNITY
- HIGH WHITE LIGHT IMMUNITY
- ADJUSTABLE PULSE COUNT
- ADJUSTABLE RANGE
- LONG LIFE LITHIUM BATTERY SUPPLIED
- LOW BATTERY WARNING SIGNAL
- HOURLY SUPERVISION RADIO SIGNALS
- SEPARATE BATTERY COMPARTMENT
- AUTOMATIC TEST MODE DISABLE

QUANTUM™ R12 RADIO PIR

The Ness Quantum™ R12 radio PIR is a purpose built radio detector especially designed for the latest generation of Ness radio control panels.

The R12 is fully compatible with all Ness radio receivers and radio capable control panels. Radio supervision is also available when used with compatible Ness control panels via the Ness 100-200 Radio Interface, or direct to the Ness R8 panel.

With a detection range of 12 metres with high immunity to RF and white light interference, adjustable pulse count and adjustable sensitivity, the R12 is the ideal radio PIR for most domestic and commercial wireless installations.



The R12 is powered by and supplied with a long life lithium 9V battery. The battery compartment can be accessed from the front of the detector, without having to remove the detector from the wall or expose the internal electronics.

SPECIFICATIONS

Dimensions	99(h) x 79(w) x 48(d) mm
Mounting height	2.1m
Coverage	12m x 12m @ 90°
Detector zones	20 dual element zones
Pulse count	Selectable 1-2 or 3-4
Range	Selectable High/Low
Sensor	Dual element pyroelectric
Visual display	Red alarm LED
Alarm period	5 seconds
Warm up period	30 seconds
Operating voltage	7-9V DC
Battery	9V Lithium, Ultralife U9VL, (supplied)
Quiescent current draw	16µA
Radio transmitter	SAWR stabilised
Radio frequency	303.875MHz
Transmit power	100µW PEP
Compatibility	Ness D8, D16, D24 panels via the 100-200 Ness Radio Interface. Ness R8 panel. Ness 100-666 MCR receiver. Ness 100-187 SCR receiver.



NESS SECURITY PRODUCTS
Australian Communications Authority
RADIO COMMUNICATIONS COMPLIANCE

Part No. 100-691 Ness R12 Radio PIR

Photographs are used for illustrative purposes only. Design and specifications may vary.
© 2002 Ness Security Products Pty Ltd ABN 28 069 984 372



Security Products

SYDNEY 02 8825 9222	MELBOURNE 03 9878 1022	BRISBANE 07 3343 7744	PERTH 08 9328 2511	ADELAIDE 08 8277 7255	NZ (NFS SECURITY) +64 9 573 0401	HONG KONG +852 2721 8097
-------------------------------	----------------------------------	---------------------------------	------------------------------	---------------------------------	--	------------------------------------